



Solar Charger Controller CC-10000

IC-CC10000

- This charge controller is a perfect match for solar panels generating up to 10A of current.
- It works with all 12V battery systems and it's intelligent PWM (Pulse Width Modulation) feature ensures batteries reach max. capacity.
- The built-in LED indicator instantly displays charging status.
- Nominal Voltage: 12V
- Max Array Voltage (Voc) 30V
- Continuous Charging Current: 10A
- Temperature Range: -40 to 50 °C (-40 to 122 °F) For indoor use only.



- Avoids Solar panel overcharging of battery systems
- Integrated screw terminal connections for quick and easy installation
- Simple to follow logos for worry free battery and Solar panel connection.
- Built in Surge protection and automatic reset for battery protection and continuous hassle free operation.
- Reverse polarity protection, battery will not be damaged if Negative and Positive wires are switched.
- Reverse current protection, blocking diode prevents your batteries from draining at night.
- Low self power consumption so that more power will be stored in your battery.

SUNSEI® My Solar Lifestyle

SPECIFICATIONS

Model number	CC-10000
Item number	IC-CC10000
UPC code	775540111003
Maximum Current	10A
Case protection	IP22
Warranty	2 years warranty
Certification	CE

THE BOX INCLUDES

- 1 Charge controller CC10000
- 1 Multi-Lingual instruction manual

WEIGHTS AND DIMENSIONS

Dimensions	2.2" X 2.8" X 1.1" 5.7 cm x 7.0 cm x 2.8 cm
Weight	0.26 lbs 0.12 kg