



Solar Charger Controller CC-25000

- Perfect match for solar panels generating up to 25A of current.
- It works with all 12V battery systems and it's intelligent PWM (Pulse Width Modulation) feature ensures batteries reach max. capacity.
- Multiple LED indicators show the charge status and battery condition
- Nominal Voltage: 12V / 24 V
- Max Array Voltage (Voc) 30V / 50 V
- Continuous Charging Current: 25A
- Temperature Range: -40 to 50 °C (-40 to 122 °F) For indoor use only



- Avoids Solar panel overcharging of battery systems
- Integrated screw terminal connections for quick and easy installation.
- Simple to follow logos for worry free battery and Solar panel connection.
- Built in Surge protection and automatic reset for battery protection and continuous hassle free operation."
- Reverse polarity protection, battery will not be damaged if Negative and Positive wires are switched."
- Reverse current protection, blocking diode prevents your batteries from draining at night.
- Low self power consumption so that more power will be stored in your battery.

SUNSEI® My Solar Lifestyle

SPECIFICATIONS	
Model number	CC-25000
Item number	11101
UPC Code	7 75540 11101 0
Maximum Current	25 A
Case protection	IP22
Warranty	2 years warranty
Certification	CE
THE BOX INCLUDES	
1 Charge controller CC-25000	
1 Multi-Lingual instruction manual	
WEIGHTS AND DIMENSIONS	
Dimensions	4" x 3 1/8" x 1 3/8" 10.16cm x 7.95cm x 3.51cm
Weight	1 lbs 0.45 kg